


Dimmer compatibility LED

	Good dimming
	Good dimming. Some slight flickering in lower or higher levels may occur
	Dimming is not very smooth and/or flickering during a non definite part of the dimming range may occur
	Dimming not possible



Brand	Model	Type	load	load type	min	max	low
BERKER	2873		20-500	RL	1	9	90%
BUSCH-JAEGER	6523U		2-100	RLC	1	9	70%
BUSCH-JAEGER	6513U	Tronic	40-420	RC	2	9	70%
Calex	2483HC	LED	3-70W	RC	1	9	80%
GIRA	226200		20-500	RL		UNSUITABLE	
INTERTEK	68.40.99.07.99	LED	5-150	RC	1	9	100%
JUNG	1730DD	LED	3-60W	RLC	1	9	90%
JUNG	1731DD	LED	3-100	RLC	1	9	90%
KLEMKO	D-PAF-200	LED	1-200	RC	2	9	70%
LEGRAND	7 525 60	LED	5-75	RLC	3	9	80%
LEGRAND	48871	LED	1-150		2	9	90%
LUMEO	T39.07	Triac	3-100	RL	1	9	100%
PEHA	431 HAN LED	LED	06-60	RL		UNSUITABLE	
Schneider	SBD315RC	Tronic	20-315	RC	2	9	80%
SPL	960000101	LED	5-200/300	RL/RC	1	9	100%
SPL	960175101	LED	2 - 175	RL/RC	1	9	100%
TRADIM	2485H	LED	0-70	RC	1	9	100%
TRADIM	2490HP-exop	Tronic	5-150	RC		UNSUITABLE	
TRONIX	215-131	LED	10-350	LED	2	9	90%
YPHIX	D350EX	LED	5-350	RC	2	9	90%
NIKO	310-0190X	LED	5-325	RLC	2	9	80%

Information presented is meant to serve as a general guideline only. Tests were conducted on 1 single dimmer in our Laboratories. True 1:1 dimmer compatibility can only be determined on-site under actual conditions and within the final application. Results can differ from dimmer to dimmer of even the same type number and brand. Please contact your local representative or a recognized electrical installer if any additional information is required.