

L028522040

LED G8.5 T30x105mm 230V 2100Lm 18W
4000K 840 360° AC Helder Dimbaar

**Specials & Projecten, G8.5 230V
Premium**



General		Energy															
Eprel registration no	1604491	Operating voltage	230 V														
Socket	G8	Volt	220..240 V														
Bulb shape	T30	Frequency	50..60 Hz														
Width	30.00 mm	Watt	18 W														
Depth	30.00 mm	Current type	AC														
Height	105.00 mm	Power factor	0.95														
Finish	Clear	Energy efficiency class	E														
Colour	Colourless	Energy consumption	18 W														
Body material	Polycarbonat	Replacement wattage	131 W														
Lifespan	25000 hours	Lamp efficacy	116.67														
Switches	15000	<div>LED</div> <table><tr><td>Filament LED</td><td>No</td></tr><tr><td>LED type</td><td>SMD 2835</td></tr><tr><td>Dimm type</td><td>Trailing and leading edge</td></tr><tr><td>Number of leds / sticks</td><td>120</td></tr><tr><td>Colour consistency SDCM</td><td>SDCM5</td></tr><tr><td>Dim to warm</td><td>No</td></tr><tr><td>Adjustable beam angle</td><td>No</td></tr></table>		Filament LED	No	LED type	SMD 2835	Dimm type	Trailing and leading edge	Number of leds / sticks	120	Colour consistency SDCM	SDCM5	Dim to warm	No	Adjustable beam angle	No
Filament LED	No																
LED type	SMD 2835																
Dimm type	Trailing and leading edge																
Number of leds / sticks	120																
Colour consistency SDCM	SDCM5																
Dim to warm	No																
Adjustable beam angle	No																
Beam angle	360 °																
Dimmable	Yes																
Degree of protection	IP20																
Net weight	0.089 kg																
Warranty	2 years																
Light		Ordering details															
Kelvin	4000 K	L028522040	Quantity pc(s) EAN														
Colour temp nr	840	Single package	1 8718739070851														
Stable lumen	2100 lm	Outer carton	100 28718739070855														
Color Rendering Index (CRI)	80																
Remark																	
Replace existing lamps with these 230V mains-powered LED's by removing the ballast and connecting the lamp holder on 230V mains																	